



SET UP OF TELESTAR SR2HC 12/24/230 volt STB

- Press Menu
- Change language to “English” with volume up or down buttons
- Select ports A,B,C,and D to None
- OK
- Select Satellite to “Newsat 010.0E”
- Select LNB to either 10.750 or 11.300 depending on your LNB LOF. With volume buttons
- Select Search all Types to FTA
- Select Manual Search with “RED” button on Remote control.
- Select “Newsat 101.0E”
- Network to Search to “ON”
- Frequency to 12483
- Symbol Rate 22500
- Polarization to “Horizontal”
- OK
- The receiver will load both 12483 and 12456 automatically.
- Time Setting, Select System Management.
- Timer Setting
- Local Time to 0 Hours
- Summer time to OFF
- OK and OK again to SAVE.
- To Move Channels in the Program List
- Press Menu
- Channel management, OK
- Select Green button on remote
- High light the program to be moved, OK, two small arrows appear beside this program
- Scroll with PR+ or PR- Buttons to the new position
- OK
- Exit then OK to SAVE.
- Please note that if you install a new pass word we will not be able to enter the receiver to service it if you can not remember it. Always leave it at 0000. Or 5565.
- If you have pressed the MENU button and a window appears asking for a password please press the BACK button.